VC-TR61_VC-TR61N Firmware(FW) Update Manual

1 Device and Tool Preparation

1.1 Please prepare following devices and tools before FW upgrade.



2 Connections

2.1 Connecting via switch or router.



3 FW Update Instructions

- (X) VYW100 -> VYW107 or later version (Not compatible)
- (O) VYW100 -> MED003 -> VYW107 (Compatible)
- (O) VYW101 -> VYW107 or later versions (Compatible)
- (O) VYW107 -> VYW108 or later versions (Compatible)

4 FW Download

4.1 Open browser and enter the IP address of the camera in the address bar.You can check the IP address from [Status]> [Ethernet] in the menu.



4.2 Enter the account and password to log in webpage. Account: admin Password: 9999(Default)

	Lumens
ዲ 6	User name
	Remember Me
	English Login

4.3 Select [Maintenance]> [...] to select firmware file and press [Upgrade].

🚔 Live View	Maintenance		
(intersection) (inter	Firmware Update		Ungrade
أ¢ Audio			upyraue
((••)) Stream	Factory Reset	Reset Reboot	
🔅 System <	Configuration	Export Import	
🔧 Maintenance	Event Log	Export	
1 About			
HEVC Advance"			

FW054 - VC-TR61_VC-TR61N FW Update Manual

4.4 FW download starts, please don't close the page. (Around 2-3 minutes taken)

Firmware Update		N12Y V2 0 0 D 2023	10920 WYY020H	Ungrade	
		NT2A_V2.0.0_K_2023	0320_07102011	opgrade	
Factory Reset	Reset	Reboot			
Configuration	Export	Import			
Event Log	Export		Message		
			Do you want to update	your Firmware? It takes	
			2-3 minutes to finish th	ne update.	
			Yes		
Firmware Update	CK812_NDI_U	IN12X_V2.0.0_R_2023	0920_VXY020H	Upgrade	
Factory Reset	Reset	Reboot			
Configuration	Export	Import			
Event Log	Export				
		M	lessage Please do not remove the power o	during the firmware update !	
					J
Firmware Updat	CK812_NDI	_UN12X_V2.0.0_R_20	0230920_VXY020H	Upgrade	
Factory Reset	Reset	Reboot			
Configuration	Export	Import			
Event Log	Export		Message		
			Restart System & In minute then refresh	itialization, Please wait 1 web page.	
				Confirm	

4.5 Login webpage again and check the FW version from [About]> [Firmware Version].

Lumens	
Live View	
() Tracking	Lumens
الله Audio (ال	
(•••)) Stream	Manufacturer : Lumens Digital Optics Inc.
🖨 System <	Model Name : VC-TR61 Firmware Ver. : VYW055
✤ Maintenance	MAC Address : E4:77:D4:AB:68:1D Serial Number : 00001A
1 About	
	www.MyLumens.com
HEVCAdvance"	